# Steca PA HS200 Accessories for Steca Power Tarom

### Shunt

The Steca PA HS200 is a highly intelligent current sensor with extremely low own consumption.

The Steca PA HS200 comes into play when (e.g.) an inverter is directly connected to the battery and the Steca Power Tarom charge controller cannot measure the current consumption. A shunt is also required when an additional generator (e.g. PV, wind or diesel) directly charges the battery without being connected to a Steca Power Tarom charge controller. The current is measured contact-free via a Hall-effect sensor. The data is transmitted to the charge controller over a cable connection. Up to two Steca PA HS200 shunts can be connected and the measured currents can be selectively added to the charging current, battery current or load current as desired.



- **Product features**
- · Automatic detection of voltage
- · Potential free current measurement
- · Communicates and stores data in the Steca PA Tarcom
- Integrated Hall sensor

## Displays

- LED shows operating states
- $\cdot\,$  Messages via Steca Power Tarom LCD display

#### Interfaces

• Two RJ45 cable sockets

## Modes of operation

- · »Battery«: measures currents which flow through the
- to the charge controller
- »Charge«: measures currents of back-up generators

#### Certificates

- · Compliant with European Standards (CE)
- · Developed in Germany



|   | PA HS200                                       |
|---|--|
| Characterisation of the operating performance |  |
| System voltage                                | 10 V 65 V                                      |
| Own consumption                               | < 9 mA   |
| Measurement accuracy                          | (-20 A +20 A) +/-1 %<br>(-200 A +200 A) +/-3 % |
| Operating conditions                          |  |
| Ambient temperature                           | -15 °C +50 °C                                  |
| Relative humidity                             | 75 %   |
| Fitting and construction                      |  |
| Current range "battery" mode                  | -200 A +200 A                                  |
| Current range "charge" mode                   | 0 A +200 A                                     |
| Current range "load" mode                     | -200 A 0 A                                     |
| Degree of protection                          | IP 22  |
| Dimensions (X x Y x Z)                        | 100 x 60 x 25 mm                               |
| Weight  | 120 g  |
| Max. diameter for battery cable               | 19 mm  |

Technical data at 25 °C / 77 °F

