

Steca PA IRS 1008/180

Motion detector

The Steca PA IRS 1008/180 motion detector is connected to the load output of the night light charge controller. This supplies power to the light, which is then turned on for a few minutes when some movement is detected.

The Steca PA IRS 1008/180 stands out, above all, with its extremely low own consumption, and is therefore optimal for use in solar power systems.



PA IRS 1008/180	
Characterisation of the operating performance	
Own consumption	6 mA
Turn on time	1 min. ... 5 min.
DC output side	
Battery voltage	12 V
Load current	5 A
Fitting and construction	
Reach / detection area	7 m / 180°
Degree of protection	IP 65

Technical data at 25 °C / 77 °F

Areas of application:

